# JITONA

## 4+2 chest of drawers



## Please read these instructions before use and retain for future reference

If you need help with this product, please contact our helpline on **Freephone 0870 160 1490** Your statutory rights are not affected.

Page 1/12

Produced in the Czech Republic

Document number 11-9M-301/3

#### Caution!

- Adult assembly required.
- Two-person assembly recommended.
- This item contains small parts that have sharp points and edges in the unassembled state. Keep away from children.
- Always place furniture on a firm level base.
- Do not stand or jump on this furniture.
- Do not assemble this furniture with a power tool.
- After assembly dispose of all packing materials safely.

#### Before assembly:

- Please read all instructions before beginning assembly.
- Please note this could be dangerous if incorrectly installed.
- Unpack and assemble this furniture, on a protective surface, in the room it will be used.
- Save all packing materials until assembly is complete to avoid accidentally discarding smaller parts or hardware.

#### Tools required

Cross head screwdriver (long reach) Pencil / Ruler / Spirit level / Masking tape / Hammer Dril fitted with a Ø 8mm drill bit (as required for the wall type)

#### Parts

i uito					
A	В	С	D	E	F
	( <u> </u>	·			
Top panel	Plinth	Middle panel	Left side panel	Right side panel	Back panel
1	1	1	1	1	1
G	Н	I	J	K	L
<u></u>	<u></u>	<u></u>			
Front board	Bottom back board	Reinforcement	Drawer front panel	Drawer front panel	Drawer back panel
4	1	1	4	2	4
М	N	0	Р	Q	
	$\bigcirc$	$\langle \rangle$		$\sim$	
Drawer back panel	N Drawer bottom panel	Drawer bottom panel		Drawer R side panel	
	$\bigcirc$	$\langle \rangle$		$\sim$	
Drawer back panel	Drawer bottom panel	Drawer bottom panel	Drawer L side panel	Drawer R side panel	
Drawer back panel	Drawer bottom panel	Drawer bottom panel	Drawer L side panel	Drawer R side panel	f

				A)	0-1111111
Wooden dowel	Wooden dowel	Cam bolt	Cam lock	Cam lock	Plastic dowel
( Ø6x30mm)	( Ø8x30mm)		( Ø15x12mm)	( Ø12x10mm)	
12	20	44	20	24	24

g	h	i	j	k	
O	8 <u>6 6 6 6 6 6 6 6 6 6 6 6 6 6 6 6 6 6 6</u>	00 00 0 00 R 0 000		<u> </u>	£
Nail	Runner left A	Runner right A	Screw ( ∅6,3x10,5mm)	Runner left B	Runner right B
40	6	6	24	6	6
m	n	0	р	q	r
\$200		A A A A A A A A A A A A A A A A A A A		(8)	0
Screw	Feet	Drawer base support		Screw	Underlay
(Ø3x16mm)			( 12x150mm)	( Ø3,5x13mm)	( Ø15mm)
24	4	12	1	1	1
S	t				

0	
Socket head screw	Socket head key
( Ø7x50mm)	(L4mm)
1	1

#### **Care Instructions**

- Clean surface with a slightly damp cloth and wipe dry using a soft cloth.
- Do not use detergents, abrasive cleaning products or cleaning products which may contain ammonia or solvents, as these may damage the surface finish.
- To properly protect wood, it must not be exposed to excessive heat or humidity.
- Periodically check and tighten all fixings.

## Check all parts and fittings are present before starting to assemble

In the unikely event that the parts supplied are damaged or missing, please contact the helpline on 0870 160 1490 for a replacement. Your statutory rights are not affected.

1 int	2	<b>4</b>	5 6	<b>7</b>
<b>1 2</b> cm <b>3 4</b>	5 6 7 8	9 10 1 2	3 4 5	6 7 8
Page <b>3/12</b>			Document number	11-9M-301/3

## Assembly





- Position left runner A (h) and right runner A (i) on to the drilled holes of the left / right side panel (D&E) and middle panel (C).
- Fix through holes shown using screws (j).

1 int 2 3 4 5 6 7 8 9 10 1 2 3 4 5 6 7 8 Page 4/12 Document number 11−9M−301/3





$ \begin{array}{ c c c c c c c c c c c c c c c c c c c$	<b>7</b>
	6 7 8
Page 6/12 Document number	11-9M-301/3



• Before fixing the back panel (F), the diagonal lines must be equal. ("a" to "a" and "b" to "b")



Page 7/12 Document number 11-9M-301/3





 Attach drawer front panel (J&K) to the drawer left / right side panel (P&Q) with wooden dowel (a), then insert cam lock (e) into the holes as pictured on the underside of drawer left / right side panel (P&Q) and tighten.

 1
 int
 2
 3
 4
 5
 6
 7

 1
 2
 3
 4
 5
 6
 7
 8
 9
 10
 1
 2
 3
 4
 5
 6
 7
 8

 Page
 8/12
 Document number
 11-9M-301/3
 11-9M-301/3
 11-9M-301/3
 11-9M-301/3



Page **9/12** 

Document number 11-9M-301/3



- Position left runners B (k) and right runners B (l) on to the left / right side panel (P&Q).
- Fix using screws (m).
- Positions 2 drawer base supports (o) onto the large drawers as shown. Fix using supplied screw.

1 int 2 3 4 5 6 7 8 9 10 1 2 3 4 5 6 7 8 Page 10/12 Document number 11−9M−301/3



- Mark fixing hole onto wall. Drill a hole and insert a suitable wall plug. Fix wall strap (h) using a suitable screw.
- *Note:* Wall fixings are not supplied with this unit.
- The correct type of fixing must be used for your wall, seek professional advice if in doubt.



